

The wise choice



Micro-Tronics

for all your filter needs


Micro-Tronics is an operating division of O.M. Jones, Inc.

Telephone: 209-532-1008

Facsimile: 209-532-1009

e-mail: sales@micro-tronics.net

-Model HPM50114



DIMENSIONS ARE IN INCHES (MM)

Micro-Tronics Model HPM50114 was specifically designed to reject DC to 1000 MHz and passing 1500 MHz while maintaining low insertion loss and a broad upper passband. The basic highpass filter design can also be adapted to custom applications.

Specifications:	
Passband (MHz)	1500 to 18000
Passband Insertion Loss:	1.5 dB maximum
Passband VSWR:	2.0:1 maximum
Stopband:	50 dB min from 0 to 1000
Operating Power:	2W max

Connectors:

Model #:

HPM50114:	SMA Female – SMA Female
HPM50114-01:	SMA Male – SMA Female
HPM50114-02:	SMA Female – SMA Male
HPM50114-03:	SMA Male – SMA Male